

**BIG DIGITAL DISPLAY WITH
LIVE RECORDING & ECHO EFFECT**



MODEL	RXA - 350 DP ECHO	RXA - 185 DP ECHO	RXA - 150 DP ECHO
Power Output	500W Max, 300W RMS at 10% THD	200W Max, 175W RMS at 10% THD	180W Max, 150W RMS at 10% THD
Input Channel	6x Mic: 2mm / 4.7KΩ, 2x Aux: 100mm / 470KΩ Line In 1V / 50KΩ	5x Mic: 2mm / 4.7KΩ, 2x Aux: 100mm / 470KΩ Line In 1V / 50KΩ	4x Mic: 2mm / 4.7KΩ, 2x Aux: 100mm / 470KΩ Line In 1V / 50KΩ
Digital Player	Mp3 Player, Recorder / FM Radio with Remote control USB / SD Card & MMC Card Reader with Bluetooth		
Frequency Response	50-15000Hz ± 3dB	50-15000Hz ± 3dB	50-15000Hz ± 3dB
Tone Control	Bass ± 10dB at 100Hz, Mid ± 10dB at 1KHz, Treble ± 10dB at 10KHz		
Echo	Delay & Repeat control for echo (Mic 1 & Mic 2)		
Out Put	Line Out 1V / 1KΩ, Preout 200mV / 600Ω		
Output Regulation	≤ 2dB no Load to Full Load at 1KHz		
Signal to Noise Ratio	60dB		
Speaker Outputs	2Ω, 4Ω, 8Ω, (for direct connection) 70 & 150V Line (for use with LMT)	4Ω, 8Ω, (for direct connection) 70 & 150V Line (for use with LMT)	4Ω, 8Ω, 16Ω (for direct connection) 70 & 150V Line (for use with LMT)
Power Supply	230V AC, DC 30V (12x2 Car Battery)	230V AC, DC 30V (12x2 Car Battery)	230V AC, DC 12V (12x1 Car Battery)
Cooling	DC Fan Cooling		

Frequency Response

50-15000Hz + 3dB

Amplify your Voice with *Real Audio*

WITH ECHO EFFECT

E-mail: info@realaudiosystem.com,
Website: www.realaudiosystem.com

RXA-150 DP ECHO



RXA-185 DP ECHO



RXA-350 DP ECHO

