

CPA 8000

WIRELESS MICROPHONE SERIES



TRANSMITTER (handheld/bodypack)

- * Channels: 200channels
- * Bandwidth: 50MHz
- * Channel space: 250KHz
- * Frequency stability: $\sim 0.005\%$
- * FM Max frequency adjusting: $\sim 45\text{KHz}$
- * RF output: HIGH 10mW / LOW 5mW
- * Power supply: 2*AA batteries

RECEIVER

- * Operating frequency: 470-786MHz
- * Channels: 4*100channels
- * Bandwidth: 50MHz
- * Channel space: 250KHz
- * ACR/IR SYNC and scan technology
- * Battery display on LCD
- * S/N ratio: $> 105\text{dB}$
- * T.H.D distortion: $< 0.5\%$
- * Frequency response: 20Hz-18KHz
- * Distance: 50-80 meters approx

