

**NEWLY
LAUNCHED**

K2 SERIES

POWER AMPLIFIERS

SWETON®



POWER OUTPUT

Model	K2-H3000			K2-H5000		
Number of channels	2			2		
Total output all channels driven	3000 W @ 4 ohms			5000 W @ 4 ohms		
Max. Output Power	2 ohms	4 ohms	8 ohms	2 ohms	4 ohms	8 ohms
Per channel watt	2000 W	1500 W	1000 W	3400 W	2500 W	1500 W
Bridge Mono	-	3000 W	2000 W	-	5000 W	3000W

Frequency Response

±0.1 dB from 20 Hz to 20 kHz at 1 watt

Phase Response

±10 degrees from 10 Hz to 20 kHz at 1 watt

THD

0.05% THD @ 100 mV RMS, 1 kHz sine wave

Damping Factor

>2000 from 10 Hz to 400 Hz